




**PANASONIC**

# Panasonic 5015 display board for EBL512 G3 panels 5000S/5001S

Product code 42624 · Fire alarm systems > Control equipment

Display board (MMI board) for Panasonic EBL512 G3 fire alarm control panels 5000S. The board sits behind the panel's front door and connects the main board to the LCD display, the front panel LEDs and keypad, the loudspeaker and the printer.

- Spare part for 5000S series EBL512 G3 panels
- Connections for LCD display 5038, loudspeaker 5036 and printer 5058
- Connections for the LEDs and keypad of front panel 5060/5061
- Adjusters for display contrast and loudspeaker volume
- Replaces the earlier display board 5011



## Product description

Panasonic 5015 is the display board, or MMI board (user interface board), of the EBL512 G3 fire alarm control panel. The 5000S series control panels have the 5012 main board and the 5015 display board. The board is located on the back of the control panel's front door and is intended as a spare part.

## Connections

- J1: main board
- J9 and J4: LCD display 5038
- J2 and J3: front panel 5060/5061 (LEDs and keypad)
- J7: loudspeaker 5036
- J6: printer 5058

The board has potentiometers for the LCD display contrast (VR2) and the loudspeaker volume (VR1), start and boot buttons, and a status LED that is lit in normal mode.

## Replacement

The software version of the display board must match the version of the main board exactly. When the earlier 5011 display board is replaced with the 5015 board, the LCD display cable is routed from behind the board through the hole in the board before installation. Make sure that the cable locks into the connector and that the ferrite supplied is fitted.

## Technical data

|               |                                                                                        |
|---------------|----------------------------------------------------------------------------------------|
| Product code  | 42624                                                                                  |
| Manufacturer  | Panasonic                                                                              |
| Product group | Fire alarm systems > Control equipment                                                 |
| Connection    | J1 main board, J9/J4 LCD 5038, J2/J3 front panel, J7 loudspeaker 5036, J6 printer 5058 |
| Adjustments   | LCD contrast (VR2), loudspeaker volume (VR1)                                           |
| Mounting      | On the back of the panel's front door                                                  |
| Compatibility | EBL512 G3 5000S series, main board 5012; replaces board 5011                           |

## Documents

The manufacturer's original documents can be downloaded from the product page (QR code at the top of this sheet).

**Technical datasheet (series):** EBL512 G3 5000 and 5001

### Request a quote or ask for more information

Sales +358 40 668 7641 · [myynti@pap.fi](mailto:myynti@pap.fi) · Mon–Fri 8 am – 4 pm (Finnish time)

Up-to-date information and documents: [pap.fi/en/tuote/panasonic-5015-nayttokortti-eb1512-g3-5000s-5001s/](https://pap.fi/en/tuote/panasonic-5015-nayttokortti-eb1512-g3-5000s-5001s/)