



EMEX

MX40 Red X

Product code 970021 · Emergency lighting > MX luminaires

Red cross panel for the MX40 RX exit sign. The panel is fitted on top of the pictogram, and the fire alarm control panel lights a red X on it when the route is closed.

- Shows a red X to indicate a blocked exit direction
- Only for MX40 RX bodies (840101, 840301, 840303)
- Controlled from the fire alarm control panel according to the alarm point or zone
- Fitted on top of the pictogram with the plastic buttons supplied
- Size 400 × 200 mm

Product description

MX40 Red X is a red cross panel for MX40 RX exit signs. The panel is fitted on top of the ordinary pictogram. In normal mode the sign shows the escape route in the usual way, but when an alarm point or zone of the fire alarm system goes into fire alarm, a control expression in the control panel lights a red X on the sign. This directs evacuees away from a route that is dangerous, for example because of smoke. The X goes out when the fire alarm is reset at the control panel.

The panel only works in RX bodies with red X illumination: MX40 RX 1 h (840101), MX40 RX 3 h (840301) and MX40 RX Black 3 h (840303). On the RX model the pictogram is always single-sided. In EBLWin the luminaire is programmed with type MXER.

Installation

First fit the pictogram in the mounting profile of the body. Then slide the X panel on top of the pictogram, tighten the screw and lock the panel in place with the plastic buttons supplied. Finally, the body is fitted to the analogue base 3312FLW or 3312W and the sign is turned to face the correct direction. The viewing distance of the RX bodies is 40 m and the degree of protection is IP41.

Technical data

Product code	970021
Manufacturer	Emex
Product group	Emergency lighting > MX luminaires
Dimensions	400 × 200 mm
Product number (Emex)	970021
Compatibility	MX40 RX housings 840101, 840301, 840303
Fixing	On top of the pictogram, plastic clips

Documents

The manufacturer's original documents can be downloaded from the product page (QR code at the top of this sheet).

Product catalogue: Emex products and spare parts

Technical datasheet (series): MX25, MX40 and MX Light

Product brochure (series): MXER25 and MXER40
Technical datasheet (series): Emex MX40 RX

Request a quote or ask for more information

Sales +358 40 668 7641 · myynti@pap.fi · Mon–Fri 8 am – 4 pm (Finnish time)

Up-to-date information and documents: pap.fi/en/tuote/mx40-red-x/